

BALM-4A

Audio Alarm



제품사진

This unit can work as the audio signal indicator applied to multiple channels broadcasting system of all levers TV stations, the grade 10 LED with high luminance can lively monitor the working range of multiple audio signal, thereby the operator can know the working status of the audio signal more straightly, more timely, more exactly.

Feature

- *4 lines stereo balance input/output
- *4 lines audio signal can switch and monitor
- *Signal loss monitor
- *Line error timing alarm;
- *Signal volume monitor, balance adjustment

Specification

AUDIO AMPLIFIER PART

EATED POWER (80HM): 3W X 2 (THD=0.03%)
 FREQUENCY RESPONSE: 200HZ-----20K (POWER OUT)
 FREQUENCY RESPONSE: 20HZ-----20K (LINE OUT)
 S / N \geq 90dB
 1/2 POWER \leq 0.03%
 CROSSTALK \geq 70DB
 CROSSTALK \geq 90DB
 SENSITIVITY 775MV/RMS
 INPUT IMPEDANCE 20KOHM
 INPUT METHOD: BALANCE

LED LEVEL DISPLAY PART

8 CHANNEL AUDIO LED LEVEL DISPLAY
 10 SEGMENTS PER CHANNEL LED LEVEL DISPLAY
 3DB/STEP, DISPLAY RANGE: 30dB
 FREQUENCY RESPONSE: 80HZ---20KHZ 0.5BD
 LED LEVEL DISPLAY SENSITIVITY : 48.9MV

DB 值	电压值 (MV)	DB 值	电压值 (MV)
MAX +6DB	1546		

10 SEGMENT LED LEVEL (DB) DISPLAY VS VOLTAGE VALUE

1	+3DB	1094	6	-12DB	194
2	0DB	775	7	-15DB	137
3	-3DB	548	8	-18DB	97.6
4	-6DB	386	9	-21DB	69.1
5	-9DB	275	10	-24DB	48.9

ALARM

EACH OF FOUR CAN SET ALARM MODE (SET ALARM AND NOT ALARM)
 FOUR STEREO SIGNAL-BROKEN CHECK ALARM
 FOUR SHIFTS SIGNAL-BROKEN TIME SETTING: 1 MINUTE, 2 MINUTES, 3 MINUTES, 5 MINUTES.
 50 MV (ALARM SIGNAL-CHECKING SENSITIVITY: 50 MV)
 ANNUNCIATOR: BUZZER

MAINS ADAPTER: 15V-1.5A
 POWER DISSIPATION: 20W



BAEKDOO
 INTERSYSTEMS
 CO.,LTD.
 백두인터시스템(주)

TEL: 02-579-9126~8
 FAX: 02-579-9129
 E-MAIL: sales@baek-doo.com
 Homepage: www.baek-doo.com